



Ironer Folder

Ironer with length folds system

PS-60/260 PL

<u>Dimensions*</u>		<u>Machine*</u>	<u>Package*</u>		
Width*	mm	3670	3830	Roll diameter mm	600
Depth*	mm	1440	1620	Working width mm	2600
High*	mm	2030	1960	Maximum production	75-105 Kg/h**
Weight*	Kg	2050	2300	Ironing speed adjustable from	3-10 mt/min
Volume*	m ³	10,73	12,16	Smokes extraction built-in system	2x1000 m ³ /h

<u>Length folds</u>		<u>Crossfold</u>	
Lanes	Folds	Lanes	Folds
1	1-2	-	-
2	1-2	-	-

- Electrical, steam, natural gas and LPG heating
- Touch- screen control panel
- Ironing belts
- Safety hands bar device
- Alarm advises on keyboard
- Fans self-cleaning
- Ironing/folding chance at the same time on 2 independ
- Program.logic control (PLC) that allows to fold the linen according to its dimensions and to create 20 working programs
- Totally personalized folding parameters

Optional (to define at the order)

- √ Vacuum table
- √ Automatic feeder (vacuum table included)
- √ Small items stacker with 2 lines
- √ Small items stacker with 4 lines
- √ By-pass length folds
- √ Supply different than 400V ~3N + T 50Hz
- √ Remote service
- √ Double pressure on length folds
- √ Dirty and ripped linen reject
- √ Rear exit (by-pass included)


Electrical installation*

Electrical power	Kw	1,9 *
Voltage 400V ~3N + T	A	2,7 *
Voltage 230V ~3 + T	A	4,8 *

Pneumatic installation*

Compressed air needed bar	6,5	7000	NI/h
---------------------------	-----	------	------

<u>Connections</u>	<u>Compressed air</u>	<u>Electricity</u>	<u>Gas/Steam</u>	<u>Exhaust fume</u>	<u>Exhaust (Steam)</u>
Type	Ø 12 mm	5G4-400V	1"	2x120 mm	½"
X mm	150	40	190	186 / 3428	110
Y mm	0	0	0	152	0
Z mm	85	135	885	1800	885



Heating

<u>Natural gas</u>		<u>LPG</u>		<u>Steam (P max 12 bar)</u>		<u>Electrical</u>					
Consumption	m ³ /h	6,70	Consumption	m ³ /h	2,50	Consumption	Kg/h	95	Consumption	A	78
Power	Kw	63,30	Power	Kw	67,40	Power	Kw	55	Power	Kw	54

*) Optional excluded

* *) 50% residual humidity, 140 gr/m2 cotton, used roll surface 100% - The technical data can change without advice